

Amp Box DS

Stereo power amplifier

- **NEW!** Improved PWM-circuitry (Pulse Wave Modulation)
- **NEW!** Improved signal spectrum and lower distortion
- **NEW!** 2 ohms drive capability
- High efficiency from mains to audio power (92%)
- Low heat emission
- Stereo level input (RCA)
- Gold-plated 5-way speaker binding posts
- Suitable for banana/spade/pin/bare wire
- Trigger input & loop out
- Metal casing protects against vibration and interference
- Available in black or silver

technical data

| | |
|-----------------------|---|
| Output power | 2 x 100W / 180W @ 8 / 4 ohms 2 ohms drive capability |
| Frequency response | 10Hz - 50kHz (+ 0dB, - 3dB) |
| Signal to noise ratio | >-90dB (IEC -A) |
| THD | < 0,1% bei 90W |
| Line level input | 1 pair RCA/Cinch sockets |
| Input sensitivity | 1,5V |
| Input impedance | 100kohms |
| Speaker out | 4mm Ø bananas, spades or bare wire |
| Trigger 12V DC | In&Out, 2-pole jack Ø 2,5mm |
| External power supply | 48V/2,5A DC; 100 - 240V, 50/60Hz |
| Dimensions W x H x D | 103 x 72 x 144 (163mm including sockets) |
| Weight | 1400g without power supply |



Ultra compact power amplifier - efficient & audiophile!

A ultra high-efficiency Bi-Phase PWM(Pulse Wave Modulation) circuit with SMD parts gives outstanding audio performance and stays cool on the outside. Sound quality is aimed to be as close as possible to Class A tube amplifiers with their liquid and lifelike presentation. The Amp Box Mono S is micro-sized and therefore allows easy placement and can be switched on & off remotely via a trigger signal. A 45cm power-on cable is supplied for this purpose. For Bi- or Tri-amplification use, the remote power-on signal can be relayed to further units.

Front black



Rear view

- ◇ RCA Stereo
- ◇ Trigger
- ◇ Power

