

CD PLAYER

RCD-1572



Wolfson premium 24-bit/192kHz Digital to Analog Converter



iOS control App (requires connection to 15 Series RA/RC models)



Supports MP3 playback



Balanced XLR outputs



Includes remote control

Since 1982, when the CD was introduced, Rotel has been refining technology and evolving circuitry to bring you extraordinary sound from the familiar silver disc. As most music lovers have a substantial collection of compact discs, a high quality CD player is still an important part of most music systems. The RCD-1572, the outstanding CD player in Rotel's 15 series, focuses careful refinements to reveal even the most subtle nuances buried in a CD's pit spiral.

The RCD-1572 elevates performance by utilizing a purpose designed and built CD mechanism along with other circuit refinements. One of the RCD-1572's most important features is the Wolfson WM8740 digital filter/stereo digital-to-analog converter. Originally developed for high resolution sources, it is the product of extensive research and real world testing and processes digital signals up to 24-bits in length at sampling rates from 8 kHz to 192 kHz.

While word lengths and sampling speed may seem excessive for CDs delivering data at far lower rates, this high speed facility adds reserve capability to ensure proper reproduction under all circumstances. As the most crucial link between a CD's digital data and the analog world in which we listen, this converter boasts significant attributes in addition to its superb high resolution capabilities.

The post-converter analog circuitry benefits from Rotel's decades-long experiences in crafting the finest sounding pathway from the DAC's internal output to RCA and XLR rear panel connectors that bridge the gap between the RCD-1572 and down-stream components. All circuit components – resistors, capacitors, inductors – are chosen only after their positive contribution to sound quality were quantified and verified qualitatively by extensive listening sessions.

All of these circuits draw on a power supply based on an oversized custom Rotel-designed and precision-manufactured toroidal power transformer that, in turn, feeds precise rectifiers, tight-tolerance voltage regulators, and advanced Slit-Foil low-ESR storage capacitors, all globally sourced to ensure musically accurate operation under even the most demanding conditions.

This is all part of Rotel's long-proven Balanced Design Concept. It's yet another way of assuring you that the RCD-1572 evidences a level of attention that will make it part of your reference-level music system for years to come.

Get the most out of your CD collection with Rotel's compact disc players. See more at

rotel.com



RCD-1572



SPECIFICATIONS

Total Harmonic Distortion + Noise	0.002% @ 1kHz	Digital Output Load Impedance	0.5 volt, Peak to Peak 75 ohms
Frequency Response	20Hz-20kHz (±0.5 dB)	Power Requirements	
Channel Balance	± 0.5 dB	USA	120V, 60Hz
Channel Separation	> 115 dB @ 10kHz	EC	230V, 50Hz
Signal to Noise Ratio (A weighting)	> 118 dB	Power Consumption	15 watts
Dynamic Range	> 99 dB	Standby Power Consumption	<0.5 watts
Digital to Analog Converters	Wolfson 24 bit/192kHz DAC	Dimensions (W x H x D)	17 x 4 x 12 3/5 in 431 x 104 x 320mm
Analog Output Level / Impedance (0dBfs)		Front Panel Height	2U / 3 1/2 in / 88.1mm
Unbalanced (RCA)	2.2 volts / 100 ohms	Weight (net)	6.7 kg, 14.8 lb
Balanced (XLR)	4.4 volts / 200 ohms	Finish	Silver and Black